



MT6323 PMIC Technical Brief

Version: 0.1
Release date: 2013/1/10

© 2013 MediaTek Inc.

This document contains information that is proprietary to MediaTek Inc.

Unauthorized reproduction or disclosure of this information in whole or in part is strictly prohibited.

Specifications are subject to change without notice.

Document Revision History

Revision	Date	Author	Description
0.1	2013/01/10	ShangYing Chung	Initial

Table of Contents

Document Revision History	2
Table of Contents	3
1 Overview.....	4
1.1 Features.....	4
1.2 Applications	4
1.3 General Descriptions	4
1.4 Ordering Information.....	5
1.5 Top Marking Definition.....	5
1.6 Pin Assignments and Descriptions	6
2 MT6323 Packaging	12
2.1 Package Dimensions	12
Appendix	14

Lists of Figures

Figure 1-1. MT6323 VFBGA - 145L (5.8x5.8mm) pin assignment.....	6
---	---

Lists of Tables

Table 1-1. MT6323 pin descriptions	6
--	---

1 Overview

1.1 Features

- Handles all 2G/3G/smart phone baseband power management
- Input range: 3.4 ~ 4.5V
- 3 buck converters and 23 LDOs optimized for specific 2G/3G/smart phone subsystems
- Full-set high-quality audio feature: Supports uplink/downlink audio CODEC and high-power/quality audio amplifier
- 32K RTC crystal oscillator for system timing, 1.8 and 2.8V clock buffer output
- Multiple function GPIO
- Flexibility for various configurations of indicator LED current source: 4ISINK
- SPI interface
- Li-ion battery charging function
- Over-current and thermal overload protection
- Programmable under voltage lockout protection
- Watchdog timer
- Flexibility hardware PMIC reset function
- Power-on reset and start-up timer
- Precision voltage, temperature, and current measurement fuel gauge
- VFBGA - 145L package

1.2 Applications

Ideal for power management of 2G, 3G, smart phones and other portable systems.

1.3 General Descriptions

MT6323 is a power management system chip optimized for 2G/3G handsets and smart phones, especially based on the MediaTek MT6572 system solution. MT6323 contains 3 buck converters and 23 LDOs, which are

optimized for specific 2G/3G/smart phone subsystems.

MT6323 provides mono 0.7W into 8Ω, high efficiency Class AB/D audio amplifiers and flexibility for various applications of indicator LED drivers. It supports up to 4 channel LEDs with independent controlled. Flexible control includes: register mode, PWM mode and breath mode.

Sophisticated controls are available for power-up, battery charging and the RTC alarm. MT6323 is optimized for maximum battery life. It allows the RTC circuit to stay alive without a battery for several hours. The battery charger in MT6323 supports lithium-ion (Li-ion) battery and provides pre-charge indication. The charger input voltage can be up to 10V and allows USB charging, too.

Some multi-purpose pins enable MT6323 to be configured in various applications.

MT6323 adopts SPI interface and SRCLKEN control pin to control buck converters, LDOs, Class AB/D, various drivers and charger. Besides, it provides enhanced safety control and protocol for handshaking with BB.


MT6323 is available in a VFBGA - 145L package. The operating temperature ranges from -25 to +85°C.

1.4 Ordering Information

Order #	Marking	Temp. range	Package
MT6323A/A		-25 ~ +85°C	VFBGA - 145L

1.5 Top Marking Definition

MT6323A/A



DDDD: Date Code

\$\$\$\$\$\$: Random Code

1.6 Pin Assignments and Descriptions




Figure 1-1. MT6323 VFBGA - 145L (5.8x5.8mm) pin assignment

Table 1-1. MT6323 pin descriptions

Ball	Symbol	I/O	Description
A1	SYSRSTB	I	Watchdog reset from AP
A10	CHG_DM	I	USB D- for BC1.1 standard
A11	CHG_DP	I	USB D+ for BC1.1 standard

Ball	Symbol	I/O	Description
A12	VCDT	I	Fractional charger input voltage for charger detection
A13	VBAT_VPA	PWR	Battery power supply input of VPA
A14	VPA	O	SW node of VPA
A2	SRCLKEN	I	26MHz CLK enable
A3	XIN	I	1. One of 32K crystal connection port while using crystal to generate 32kHz clock 2. Tie to ground with 32kHz crystal absence
A4	XOUT	I	1. One of 32K crystal connection port while using crystal to generate 32kHz clock 2. External 32kHz clock input with 32kHz crystal absence
A5	DVDD18_IO	PWR	Power of VIO18 IO/CORE
A7	INT	O	Default: Output 0 Interrupt to BB, high active
A8	DVDD18_DIG	PWR	Power of VDIG18
A9	FSOURCE	PWR	EFUSE power source
B1	AUXADC_AUXIN_GPS	I	AUXADC input
B10	GND_ISINK	GND	GND for ISINK
B12	VPROC_FB	I	Feedback of VPROC
B14	VPA	O	SW node of VPA
B2	AVSS28_AUXADC	GND	GND for AUXADC
B5	SIM1_AP_SCLK	I	AP/PMIC SIM1 clock
B6	AUD_MISO	O	Uplink AUDIO ADC serial data
B7	SPI_CSN	I	SPI interface's chip select signal to identify which device is selected
B8	SPI_MISO	IO	SPI interface's serial data signal. Default is output only.
C10	ISINK3	O	Current sink channel 3 output
C12	GND_VPROC_FB	I	Remote sense on ground of VPROC
C14	VPROC	O	SW node of VPROC
C2	AUXADC_VREF18	O	1.8V AUXADC reference output
C3	AVDD33_RTC	PWR	RTC LDO output. Supply of RTC macro where backup battery can be added.
C4	RTC_32K2V8	O	RTC domain 32kHz clock output
C5	SIM2_AP_SCLK	I	AP/PMIC SIM2 clock
C9	ISINK1	O	Current sink channel 1 output
D1	AU_VIN2_N	I	Analog input 3 negative
D12	VPA_FB	I	Feedback of VPA
D14	VPROC	O	SW node of VPROC
D2	AU_VIN2_P	I	Analog input 3 positive

Ball	Symbol	I/O	Description
D3	AVDD28_AUXADC	PWR	2.8V power input for AUXADC
D5	RTC_32K1V8	O	VIO18 domain 32kHz clock output
D6	SIM2_AP_SRST	I	AP/PMIC SIM2 SRST
D8	SPI_MOSI	IO	SPI interface's serial data signal. Default is input only.
D9	SPI_CLK	I	SPI interface's clock
E1	CLK26M	I	26MHz CLK
E10	ISINK2	O	Current sink channel 2 output
E11	GND_VPROC	GND	Ground of VPROC
E13	GND_VPA	GND	Ground of VPA
E14	VPROC	O	SW node of VPROC
E2	ACCDDET	I	Accessory detection input
E4	AU_VIN0_P	I	Analog input 1 positive
E6	SIM1_AP_SRST	I	AP/PMIC SIM1 SRST
E7	AUD_MOSI	I	Downlink DAC serial data
E8	AUD_CLK	I	26M clock (can be hopping)
E9	ISINK0	O	Current sink channel 0 output
F10	GND_VPROC	GND	Ground of VPROC
F11	GND_VPROC	GND	Ground of VPROC
F13	VBAT_VPROC	PWR	Battery power supply input of VPROC
F14	VBAT_VPROC	PWR	Battery power supply input of VPROC
F2	AU_MICBIAS0	PWR	Microphone bias for main and 2 nd microphone
F4	AU_VIN0_N	I	Analog input 1 negative
F5	GND_LDO	GND	Ground for LDO
F6	GND_LDO	GND	Ground for LDO
F7	GND_LDO	GND	Ground for LDO
F8	GND_LDO	GND	Ground for LDO
F9	GND_LDO	GND	Ground for LDO
G1	AU_HSN	O	Receiver output
G11	GND_VSYS	GND	Ground of VSYS BUCK
G13	VBAT_VPROC	PWR	Battery power supply input of VPROC
G2	AU_MICBIAS1	PWR	Microphone vias for earphone
G3	AU_VIN1_P	I	Analog input 2 positive
G4	AU_VIN1_N	I	Analog input 2 negative
G5	GND_LDO	GND	Ground for LDO
G6	GND_LDO	GND	Ground for LDO
G7	GND_LDO	GND	Ground for LDO
G8	GND_LDO	GND	Ground for LDO


Ball	Symbol	I/O	Description
G9	GND_LDO	GND	Ground for LDO
H1	AU_HSP	O	Receiver output
H10	GND_LDO	GND	Ground for LDO
H11	VRF18	O	VRF18 output voltage
H13	VBAT_VSYS	PWR	Battery power supply input of VSYS BUCK
H14	VSYS	O	SW node of VSYS BUCK
H2	GND_ABB	GND	GND of ABB
H4	AU_HPL	O	Headphone L-ch output
H5	GND_LDO	GND	Ground for LDO
H6	GND_LDO	GND	Ground for LDO
H7	GND_LDO	GND	Ground for LDO
H8	GND_LDO	GND	Ground for LDO
H9	GND_LDO	GND	Ground for LDO
J10	GND_LDO	GND	Ground for LDO
J12	VCN18	O	VCN18 output voltage
J13	VM	O	VM output voltage
J14	AVDD22_BUCK	PWR	Power supply input of VSYSLDO
J2	AVDD28_ABB	PWR	2.8V power input for ABB
J4	AU_HPR	O	Headphone R-ch output
J6	GND_LDO	GND	Ground for LDO
J7	GND_LDO	GND	Ground for LDO
J8	GND_LDO	GND	Ground for LDO
J9	GND_LDO	GND	Ground for LDO
K1	SPK_P	O	Positive output for internal speaker amp
K10	SIMLS2_SRST	O	SIMLS2 SRST
K11	SIMLS2_AP_SIO	IO	SIM2_AP data signal
K14	VCAMD	O	VCAMD output voltage
K3	BATON	I	Battery NTC pin for battery and its temperature sensing
K4	RESETB	O	System reset release signal
K6	GND_LDO	GND	Ground for LDO
K8	GND_LDO	GND	Ground for LDO
K9	SIMLS2_SCLK	O	SIMLS2 SCLK
L1	SPK_N	O	Negative output for internal speaker amp
L11	SIMLS2_SIO	IO	SIMLS2 data signal
L12	VIO18	O	VIO18 output voltage
L13	VCAM_IO	O	VCAM_IO output voltage
L14	VGP3	O	VGP3 output voltage

Ball	Symbol	I/O	Description
L2	GND_SPK	GND	Ground for VBAT_SPK
L4	VTCXO	O	VTLDO output voltage
L6	VMC	O	VMC output voltage
L8	VGP1	O	VGP1 output voltage
M1	FCHR_ENB	I	Force charging ENB
M10	SIMLS1_SRST	O	SIMLS1 SRST
M11	SIMLS1_AP_SIO	IO	SIM1_AP data signal
M13	VDRV	O	Charger current drive output
M14	AVDD22_BUCK	PWR	Power supply input of VSYSLDO
M2	PWRKEY	I	Power key signal
M3	VA	O	VA output voltage
M4	VIO28	O	VIO28 output voltage
M6	VCN33	O	VCN33 output voltage
M7	VIBR	O	VIBR output voltage
M9	SIMLS1_SCLK	O	SIMLS1 SCLK
N11	SIMLS1_SIO	IO	SIMLS1 data signal
N12	EXT_PMIC_EN	O	External PMIC enable (vbat domain)
N13	CHRLDO	O	Charger LDO28 output
N14	GND_VREF	GND	Ground for bandgap
N2	PMU_TESTMODE	I	PMU testmode signal (tied to GND in normal operation)
N3	VCN28	O	VCN28 output voltage
N6	VUSB	O	VSUB output voltage
N7	VCAM_AF	O	VCAM_AF output voltage
N8	VGP2	O	VGP2 output voltage
N9	VSIM2	O	VSIM2 output voltage
P1	VBAT_SPK	PWR	Battery power supply input of SPK
P12	ISENSE	I	Positive terminal for battery's charging current sensing resistor
P13	BATSNS	I	Negative terminal for battery's charging current sensing resistor
P14	VREF	O	Bandgap reference voltage
P2	VBAT_LDOS1	PWR	LDO1 vbat power
P3	VCAMA	O	VCAMA output voltage
P4	VMCH	O	VMCH output voltage
P5	VBAT_LDOS2	PWR	LDO2 vbat power
P6	VBAT_LDOS3	PWR	LDO3 vbat power
P7	VEMC_3V3	O	VEMC_3V3 output voltage

Ball	Symbol	I/O	Description
P8	VBAT_LDOS3	PWR	LDO3 vbat power
P9	VSIM1	O	VSIM1 output voltage

2 MT6323 Packaging

2.1 Package Dimensions



Item	Symbol	Common Dimensions		
		MIN.	NOM.	MAX.
Package Type		VFBGA		
Body Size	X	5.70	5.80	5.90
	Y	5.70	5.80	5.90
	X	5.70	5.80	5.90
Ball Pitch	eD	0.40		
	eE	0.40		
Total Thickness	A	-	-	1.00
Mold Thickness	A3	0.65 Ref.		
Substrate Thickness	A2	0.11 Ref.		
Substrate+Mold Thickness	A4	0.69	0.76	0.83
Ball Diameter		0.25		
Stand Off	A1	0.12	0.16	0.20
Ball Width	b	0.20	0.25	0.30
Package Edge Tolerance	aaa	0.05		
Mold Flatness	ccc	0.10		
Coplanarity	ddd	0.08		
Ball Offset (Package)	eee	0.15		
Ball Offset (Ball)	fff	0.05		
Ball Count	n	145		
Edge Ball Center to Center	X	D1	5.20	
	Y	E1	5.20	

Appendix

N/A